

350W 17R BEAM SPOT WASH 3IN1 MOVING HEAD LIGHT

MJ-1350

Channel List:

STAN (24CH)	SMAL (16CH)	DMX Value	Function
1	1	0—255	Pan
2	*	0—255	Pan fine
3	2	0—255	Tilt
4	*	0—255	Tilt fine
5	3	0—255	Pan/Tilt speed
6	4	Macro function	
		0—19	No function
		20—24	Energy saving mode (280W)
		25—29	Normal mode (350W)
		30—49	No function
		50—59	Pan and Tilt speed mode
		60—69	Pan and Tilt time mode
		70—129	No function
		130—139	Lamp ON
		140—149	Pan and Tilt motor reset
		150—189	All small motor reset
		190—199	No function
		200—209	Light reset
		210—229	No function
		230—239	Lamp OFF
		240—255	No function
7	5	Color wheel	
		0—3	Open
		4—12	White + Red
		13—20	Red + Deep Green
		21—29	Deep Green + Deep Blue
		30—39	Deep Blue + Deep Yellow
		40—47	Deep Yellow + Purple
		48—57	Purple + Light Yellow

		58—66	Light Yellow + Rose red
		67—75	Rose red + Blue-Green
		76—85	Blue-Green + Brown
		86—94	Brown + Purplish-Red
		94—103	Purplish-Red + Yellow
		104—112	Yellow + Cool white
		113—121	Cool white + Claybank
		122—127	Claybank + White
		128—129	Open
		130—134	Red
		135—138	Deep Green
		139—143	Deep Blue
		144—147	Deep Yellow
		148—152	Purple
		153—157	Light Yellow
		158—161	Rose red
		162—166	Blue-Green
		167—171	Brown
		172—176	Purplish-Red
		177—180	Yellow
		181—185	Cool white
		186—189	Claybank
		190—220	From fast to slow stream
		221—225	Stop
		226—255	From slow to fast stream
8	6	0—255	Color wheel fine
9	*	0—255	Effect speed
10	7		Static gobo wheel
		0—5	Open
		6—11	Gobo 1
		12—17	Gobo 2
		18—23	Gobo 3
		24—29	Gobo 4
		30—35	Gobo 5
		36—41	Gobo 6
		42—47	Gobo 7
		48—53	Gobo 8
		54—59	Gobo 9
		60—65	Gobo 10

	66—71	Gobo 11
	72—77	Gobo 12
	78—83	Gobo 13
	84—89	Gobo 14
	90—95	Gobo 15
	96—101	Gobo 16
	102—107	Gobo 17
	108—113	Gobo 1 shake
	114—119	Gobo 2 shake
	120—125	Gobo 3 shake
	126—131	Gobo 4 shake
	132—137	Gobo 5 shake
	138—143	Gobo 6 shake
	144—149	Gobo 7 shake
	150—155	Gobo 8 shake
	156—161	Gobo 9 shake
	162—167	Gobo 10 shake
	168—173	Gobo 11 shake
	174—179	Gobo 12 shake
	180—185	Gobo 13 shake
	186—191	Gobo 14 shake
	192—197	Gobo 15 shake
	198—203	Gobo 16 shake
	204—210	Gobo 17 shake
	211—231	Fixed pattern clockwise rotation from fast to slow
	232—234	Gobo wheel rotation stop
	235—255	Fixed pattern counterclockwise rotation from slow to fast
11	8	Rotating gobo wheel
		0—7 Open
		8—15 Gobo 1
		16—23 Gobo 2
		24—31 Gobo 3
		32—39 Gobo 4
		40—47 Gobo 5
		48—55 Gobo 6
		56—63 Gobo 7
		64—71 Gobo 8
		72—79 Gobo 9
		80—87 Gobo 10

	88—95	Gobo 11
	96—103	Gobo 12
	104—111	Gobo 1 Shake from slow to fast
	112—119	Gobo 2 Shake from slow to fast
	120—127	Gobo 3 Shake from slow to fast
	128—135	Gobo 4 Shake from slow to fast
	136—143	Gobo 5 Shake from slow to fast
	144—151	Gobo 6 Shake from slow to fast
	152—159	Gobo 7 Shake from slow to fast
	160—167	Gobo 8 Shake from slow to fast
	168—175	Gobo 9 Shake from slow to fast
	176—183	Gobo 10 Shake from slow to fast
	184—191	Gobo 11 Shake from slow to fast
	192—199	Gobo 12 Shake from slow to fast
	200—225	Gobo wheel clockwise rotation from fast to slow
	226—228	Gobo wheel rotation stop
	229—255	Gobo wheel counterclockwise rotation from slow to fast stream
12	*	Rot.gobo indexing and rotation
	0—127	Gobo Index
	128—191	Gobo clockwise rotation from fast to slow
	192—193	Gobo rotation stop
	194—255	Gobo counterclockwise rotation from slow to fast
13	9	16-facet prism rotation
	0—127	16-facet prism clockwise rotation from fast to slow
	128—129	16-facet prism rotation stop
	130—255	16-facet prism counterclockwise rotation from slow to fast
14	10	Prism
	0—19	No function
	20—48	6-facet linear prism function
	49—74	16-facet prism function
	75—255	6-facet and 16-facet prism superposition function
15	11	6-facet prism rotation
	0—127	6-facet linear prism clockwise rotation from fast to slow
	128—129	6-facet linear prism rotation stop
	130—255	6-facet linear prism counterclockwise rotation from slow to fast
16	12	Frost
	0—64	No function
	65—255	Linear frost

17	13	0—255	Zoom
18	*	0—255	Zoom fine
19	14	0—255	Focus
20	*	0—255	Focus fine
21	*	0-4	Auto-focusing
		5-128	Auto-focusing at 5m
		129—255	Auto-focusing at 8m
22	15	Strobe	
		0—31	strobe off
		32—63	strobe on
		64—95	strobe from slow to fast
		96—127	strobe open
		128—143	from fast to slow, slow off fast on
		144—159	from slow to fast, fast on slow off
		160—191	strobe on
		192—223	Random strobe from slow to fast
		224—255	strobe on
23	16	0—255	Dimmer
24	*	0—255	Dimmer fine